

MWF63J7, MWF77J7 (Low Voltage) 300G V1000 / GA500 Inverter					
CONSTANT	VALUE	CONSTANT	VALUE	CONSTANT	VALUE
A1-00	0	E1-03	F	D1-07	188
A1-01	2 Note 3	E1-04	188	D1-08	17
A1-02	0	E1-05	220	H1-01	40
A1-03	Note 2			H1-02	41
B1-01	0	E1-06	50	H1-03	5
B1-02	1	E1-07	3	H1-04	3
B1-03	0	E1-08	15 / 13	H1-05	7
B1-17	1	E1-09	1.5	H1-06	4
C1-01	35	E1-10	8 / 7	L1-01	0
C1-02	20	E2-01	Note 1	L2-01	2
C1-03	120	D1-01	11.5	L3-01	0
C1-04	80	D1-02	10.5	L3-04	0
C2-01	1.0	D1-03	17	L3-05	0
C6-01	0	D1-04	59	L8-05	0
C6-02	03	D1-05	112	L8-07	0
E1-01	220	D1-06	164		

Note 1: Enter Ampere rating of inverter

Note 2: 2220 is initialized – otherwise 0

Note 3: Set to 0 after programming

Motor wiring: Wire motor for 208V for 200V-208V

Wire motor for 240V for 220V-240V

Release Date: July 20, 2021 Revision E