

**WELDED CBW 200V - 240V (LOW VOLTAGE)**

**GPD505**

G5 CONSTANT	G5 VALUE	G5 CONSTANT	G5 VALUE
NO01	Note 1	NO20	1.0
NO02	1	NO25	50.0 (50HZ)
		NO25	60.0 (60HZ)
NO03	230.0	NO26	50.0 (50HZ)
		NO26	60.0 (60HZ)
NO04	0	NO33	0
NO10	F	NO37	11
NO12	50.0 (50HZ)	NO50	1
NO12	60.0 (60HZ)		
NO13	230.0	NO51	1
NO14	50.0 (50HZ)	NO55	2
NO14	60.0 (60HZ)		
NO16	18	NO70	0
NO18	12	NO71	200
NO19	1.0		

BRAKING TRANSISTORS 09MVBT15L = used on 15HP(1), 20HP(1), 40HP(2), 50HP(2)

09MVBT25L = used on 25HP(1), 30HP(1), 60HP(2)

Note: 10HP, 15HP, & 20HP do not require a braking transistor.

RESISTOR OVERLOAD HEATER VALUES 10HP, 15HP, & 20HP = SB15.5

09MVBT15L = SB25 09MVBT25L = SB32

Verify that transistor module is set to correct voltage and master or slave switch.

Note 1: Put in 8 to initialize to 2 wire control.

Put in 3 to program.

Put in 0 to lockout.