

**6458 & 6464 DRYER BASKET (HIGH VOLTAGE)  
V1000 INVERTER**

CONSTANT	VALUE	CONSTANT	VALUE
A1-01	2 Note 3	H1-01	40
A1-02	0	H1-02	41
A1-03	Note 2	H2-01	E
B1-01	1	H3-04	Note 1
B1-02	1	H3-13	.5
B1-03	0	H3-03	205
C1-01	3	L1-01	0
C1-02	2	L2-01	2
C2-01	1.0		
C6-01	1		
C6-02	2		
E1-01	400		
E1-03	F		
E1-04	Note 4		
E1-05	400		
E1-06	60		
E1-07	3		
E1-08	26		
E1-09	1.5		
E1-10	20		

Note 1: Adjust to get basket speed of 32 RPM with 100% speed programmed

Note 2: 2220 is initialize - otherwise 0

Note 3: Set to 0 after programming

Note 4: Moto vario CH042 (39F1923AN) or CH052 (39F1923BN) put in 78. Baldor GIF0948C (39F1923CN) put in 85.5.

Release Date: April 26, 2013

Revision C