

PULSE FLOW PUMP (HIGH VOLTAGE) V1000 INVERTER			
CONSTANT	VALUE	CONSTANT	VALUE
A1-01	2 Note 3	H1-01	40
A1-02	0	H1-02	41
A1-03	Note 2	H1-07	6
B1-01	1	H2-01	E
B1-02	1	H3-04	20
B1-03	0	H3-13	.1
B1-17	1	H3-03	100
C1-01	3	L1-01	0
C1-02	2	L2-01	2
C2-01	1.0	D1-17	60
C6-01	1		
C6-02	2		
E1-01	400		
E1-03	F		
E1-04	60 (Note 1)		
E1-05	400		
E1-06	60		
E1-07	3		
E1-08	26		
E1-09	1.5		
E1-10	20		

Note 1: Adjust to get 60.0 – 60.8 HZ when at 100% but not to exceed nameplate amps with service factor.

Note 2: 2220 is initialize - otherwise 0

Note 3: Set to 0 after programming

Release Date: July 30, 2014

Revision I