

Published Manual Number/ECN: H00000033/2000036N


- Publishing System: TPAS
- Access date: 1/16/01
- Document ECN's: Latest Available



# Kit Instruction—

## KXMIC00103

## KXMIC00104



# Please Read

## About the Manual Identifying Information on the Cover

The front cover displays pertinent identifying information for this manual. Most important, are the published manual number (part number) /ECN (date code). Generally, when a replacement manual is furnished, it will have the same published manual number, but the latest available ECN. This provides the user with the latest information applicable to his machine. Similarly all documents comprising the manual will be the latest available as of the date the manual was printed, **even though older ECN dates for those documents may be listed in the table of contents.**

When communicating with the Milnor factory regarding this manual, please also provide the other identifying information shown on the cover, including the publishing system, access date, and whether the document ECN's are the latest available or exact.

## References to Yellow Troubleshooting Pages

This manual may contain references to "yellow pages." Although the pages containing troubleshooting procedures are no longer printed on yellow paper, troubleshooting instructions, if any, will be contained in the easily located "Troubleshooting" chapter or section. See the table of contents.

## Trademarks of Pellerin Milnor Corporation

The following, some of which may be used in this manual, are trademarks of Pellerin Milnor Corporation:

Ampsaver <sup>®</sup>	Dye-Extractor <sup>®</sup>	Gear Guardian <sup>®</sup>	Milnet <sup>®</sup>	Staph-Guard <sup>®</sup>
Autolint <sup>®</sup>	Dyextractor <sup>®</sup>	Hands-Off <sup>®</sup>	Milnor <sup>®</sup>	System 4 <sup>®</sup>
Auto-Purge <sup>®</sup>	E-P Express <sup>®</sup>	Hydro-Cushion <sup>®</sup>	Miltrac	System 7 <sup>®</sup>
Autovac	E-P OneTouch <sup>®</sup>	Mildata <sup>®</sup>	Miltron	Totaltrol <sup>®</sup>
CBW <sup>®</sup>	E-P Plus <sup>®</sup>			

## Comments and Suggestions

Help us to improve this manual by sending your comments to:

Pellerin Milnor Corporation  
Attn: Technical Publications  
P. O. Box 400  
Kenner, LA 70063-0400

Fax: (504) 469-1849

## INSTRUCTIONS FOR REPLACING EPSON DISPLAY WITH OPTREX

- Wire directions for Optrex display to be used with old Mother board and Processor ●  
Must use processor board 08BSWPADT, 4 EPROMS on board.

1. On MTA-4 which plugs into the mother board, remove the wire from MTA-4/05 and insert MTA-3/07.
2. From Oprtex Buffer Board:

Wiring for machine models C4,5,6P;B & QWP.

For kit KXMIC00103- MTA-2/-5 Remove wire from this MTA plug as it is not used.


MTA 2-3--->MTD 1-3	MTA 3-4--->MTD 2-3
MTA 3-7--->MTD 1-6	MTD 3-5--->MTD 2-4
MTA 2-7--->MTD 2-9	MTA 3-6--->MTD 2-5
MTA 2-8--->MTD 2-8	MTA 3-8--->MTD 1-7
MTA 2-9--->MTD 3-9	MTA 3-9--->MTD 1-5
MTA 2-10-->MTD 2-7	MTA 3-10-->MTD 1-2
MTA 3-3--->MTD 2-2	

---

Wiring for machine models other than listed above.

For kit KXMIC00104- You may need to ground MTA 7-7 to eliminate break fault.

MTA 1-2--->WCXR-22	MTA 2-4--->WCXR-13
MTA 1-3--->WCXR-09	MTA 2-5--->WCXR-14
MTA 1-5--->WCXR-07	MTA 2-6--->WCXR-16
MTA 1-6--->WCXR-10	MTA 2-7--->WCXR-15
MTA 1-7--->WCXR-02	MTA 2-8--->WCXR-17
MTA 2-2--->WCXR-11	MTA 2-9--->WCXR-18
MTA 2-3--->WCXR-12	



This Harness is supplied with the kit and replaces the 36 pin Molex connector WCXP currently connected to the display, key board and switches.