

It is important that the end of the cable with the shield pinned in the connector be connected to the processor board. To install the cable, insert the display end of the cable into the conduit from the rear control box. You may want to use the old wires to pull the cable through. The conduit is large enough to feed the 4pin connector through.

There is also a short jumper included which needs to be installed on the display buffer board, connected between DM21 on the buffer board and CN2 on the display.

Finally, we have included 2 transceiver chips. One is to be installed in IC1 on the display buffer board. Another is for IC23 on the processor board.